

MR Multi

ML-MRMULTI multi output LED downlight



TECHNICAL DETAILS



Total power consumed: 10W
Lumen output: 900lm White,
910lm Neutral White, 880lm Warm White
Colour temperature: 6000K White,
4000K Neutral White, 3000K Warm White
IP rating: IP44
CRI: 80+
Efficacy: up to 91lm/W
Beam angle: 120 degrees
Dimmable: Yes (for dimming range see website)
Power supply: On-board
Average life: 40,000 hrs*
Warranty: 3 years (4 years for PLI)
Diameter 110 mm | Depth 64 mm | Cut-out: 90 mm
Kit includes: 1 x LED Downlight with flex & plug

*Life span is calculated on expected average life of driver



INSTALLATION INSTRUCTIONS

1. Before commencing installation or maintenance, ensure electricity is switched off at the mains
2. Remove existing downlight and disconnect old transformer OR for new installations mark and cut out 90 mm hole in ceiling
3. Set the desired colour output with the "selector switch" on the back of the downlight head (see picture below)
4. Carefully bend spring clips upwards and install new LED downlight



PLEASE NOTE

- Follow all relevant electrical and safety standards (including AS3000) – only qualified personnel should be allowed to perform installations
- Damaged by corrosion will not be honoured as materials defect claim. It is the user's responsibility to provide suitable protection against corrosive agents such as moisture, condensation and other harmful elements.
- If these regulations are not followed warranty will be void and all issues are the responsibility of the installer.
- This product has full compliance with the IC-F rating. M-Elec still recommends that an air gap is left around driver + light to ensure the maximum life span of the product is achieved. Please request test report for more details on IC-F.
- **PLEASE ENSURE YOU READ THE DIMMING CHART AND ONLY USE THE SUGGESTED DIMMERS!**
- For further information including dimming range, please visit our website www.melec.com.au